

R&S® FSx-K8 BLUETOOTH® MEASUREMENT APPLICATION

Specifications

R&S®FSW-K8
R&S®FSV3-K8
R&S®VSE-K8



Data Sheet
Version 02.00

ROHDE & SCHWARZ
Make ideas real



CONTENTS

Definitions	3
Specifications.....	4
General remarks.....	4
Frequency	4
Signal acquisition.....	4
Measurement	5
Bluetooth® Basic Rate/Low Energy measurements.....	5
Bluetooth® Enhanced Data Rate measurements.....	6
Ordering information	7
Bluetooth® measurement application	7
R&S®FSW signal and spectrum analyzer.....	7
R&S®FSVA3000 and R&S®FSV3000 signal and spectrum analyzers	7
R&S®RTO1000 and R&S®RTO2000 oscilloscopes	7
R&S®RTP oscilloscope.....	8
R&S®VSE vector signal explorer software	8

Definitions

General

Product data applies under the following conditions:

- Three hours storage at ambient temperature followed by 30 minutes warm-up operation
- Specified environmental conditions met
- Recommended calibration interval adhered to
- All internal automatic adjustments performed, if applicable

Specifications with limits

Represent warranted product performance by means of a range of values for the specified parameter. These specifications are marked with limiting symbols such as $<$, \leq , $>$, \geq , \pm , or descriptions such as maximum, limit of, minimum. Compliance is ensured by testing or is derived from the design. Test limits are narrowed by guard bands to take into account measurement uncertainties, drift and aging, if applicable.



Non-traceable specifications with limits (n. trc.)

Represent product performance that is specified and tested as described under “Specifications with limits” above. However, product performance in this case cannot be warranted due to the lack of measuring equipment traceable to national metrology standards. In this case, measurements are referenced to standards used in the Rohde & Schwarz laboratories.

Specifications without limits

Represent warranted product performance for the specified parameter. These specifications are not specially marked and represent values with no or negligible deviations from the given value (e.g. dimensions or resolution of a setting parameter). Compliance is ensured by design.

Typical data (typ.)

Characterizes product performance by means of representative information for the given parameter. When marked with $<$, $>$ or as a range, it represents the performance met by approximately 80 % of the instruments at production time. Otherwise, it represents the mean value.

Nominal values (nom.)

Characterize product performance by means of a representative value for the given parameter (e.g. nominal impedance). In contrast to typical data, a statistical evaluation does not take place and the parameter is not tested during production.

Measured values (meas.)

Characterize expected product performance by means of measurement results gained from individual samples.

Uncertainties

Represent limits of measurement uncertainty for a given measurand. Uncertainty is defined with a coverage factor of 2 and has been calculated in line with the rules of the Guide to the Expression of Uncertainty in Measurement (GUM), taking into account environmental conditions, aging, wear and tear.

Device settings and GUI parameters are designated with the format “parameter: value”.

Non-traceable specifications with limits, typical data as well as nominal and measured values are not warranted by Rohde & Schwarz.

In line with the 3GPP standard, chip rates are specified in million chips per second (Mcps), whereas bit rates and symbol rates are specified in billion bit per second (Gbps), million bit per second (Mbps), thousand bit per second (kbps), million symbols per second (Msps) or thousand symbols per second (ksps), and sample rates are specified in million samples per second (Msample/s). Gbps, Mcps, Mbps, Msps, kbps, ksps and Msample/s are not SI units.

Specifications

The specifications of the R&S®FSx-K8 Bluetooth® measurement application are based on the data sheet specifications of the following products:

- R&S®FSW signal and spectrum analyzer (R&S®FSW-K8)
- R&S®FSVA3000 signal and spectrum analyzer (R&S®FSV3-K8)
- R&S®FSV3000 signal and spectrum analyzer (R&S®FSV3-K8)

They have not been checked separately and are not verified during instrument calibration. Measurement uncertainties are given as 95 % confidence intervals. The specified errors, accuracies and uncertainties do not take into account systematic errors due to reduced signal-to-noise (S/N) ratio, uncertainties due to imperfect impedance matching, uncertainties of external measurement amplifiers and mixers, uncertainties due to a reduced measurement interval and uncertainties of the noise source. The specified errors, accuracies and uncertainties apply at calibrated measurement frequency points.

General remarks

This data sheet covers the R&S®FSW-K8, the R&S®FSV3-K8 and the R&S®VSE-K8.

The R&S®FSW-K8 runs on the R&S®FSW. The R&S®FSV3-K8 runs on the R&S®FSVA3000 or R&S®FSV3000.

The R&S®VSE-K8 runs on a PC that is connected to the devices as specified below.

If not stated otherwise, the data sheet values are device-specific, i.e. the same value applies to the R&S®FSW-K8 and the R&S®VSE-K8 with connected R&S®FSW. Accordingly, the same value applies to the R&S®FSV3-K8 and the R&S®VSE-K8 with connected R&S®FSVA3000 respectively R&S®FSV3000.

Overview

		R&S®FSW	R&S®FSVA3000/ R&S®FSV3000	R&S®FSVA/ R&S®FSV	R&S®RTO	R&S®RTP
R&S®FSW-K8	runs on device	•	–	–	–	–
R&S®FSV3-K8	runs on device	–	•	–	–	–
R&S®VSE-K8	runs on PC that is connected to device	•	•	•	•	•

Frequency

Frequency range	R&S®FSW-K8	same as R&S®FSW
	R&S®FSV3-K8	same as R&S®FSVA3000/R&S®FSV3000
	R&S®VSE-K8	same as the connected device

Signal acquisition

Input		RF, file
Triggering	RF input	free run, external, IF power, RF power

Measurement

Supported standards		Bluetooth® 5.3 – Basic Rate
		Bluetooth® 5.3 – Enhanced Data Rate
		Bluetooth® 5.3 – Low Energy
Supported power classes		classes 1 to 3
Packet type detection	Basic Rate	DHx, DMx
	Enhanced Data Rate	2-DHx, 3-DHx, 2-EVx, 3-EVx
	Low Energy	test packet for Low Energy 1M, Low Energy 2M, Low Energy coded, each without CTE
Display types	Basic Rate	RF spectrum, RF envelope, result summary, demodulation waveform, symbols
	Enhanced Data Rate	RF spectrum, RF envelope, result summary, constellation, symbols
	Low Energy	RF spectrum, RF envelope, result summary, demodulation waveform, symbols
In-band spurious measurement	Basic Rate	20000 trace points
	Enhanced Data Rate	trace points depending on gate length
	Low Energy	20000 trace points

Bluetooth® Basic Rate/Low Energy measurements

Level		
Level range	RF input, average and peak power in line with Bluetooth® RF test specification 5.3, 5.1.3; packet type: DH1, DH3, DH5	-70 dBm ¹ to +30 dBm
Level uncertainty	R&S®FSW-K8	same as R&S®FSW
	R&S®FSV3-K8	same as R&S®FSVA3000/R&S®FSV3000
	R&S®VSE-K8	same as the connected device
Frequency deviation		
Deviation range	average and peak power in line with Bluetooth® RF test specification 5.3, 5.1.9; packet type: DH1, DH3, DH5; payload type: f1 or f2	±250 kHz
Uncertainty	average value per packet, level > -30 dBm	< 3 kHz (nom.)
Initial carrier frequency tolerance (ICFT)		
Deviation range	in line with Bluetooth® RF test specification 5.3, 5.1.10; packet type: DH1	±250 kHz
Uncertainty	R&S®FSW-K8, level > -30 dBm	< 2 kHz + R&S®FSW frequency uncertainty (nom.)
	R&S®FSV3-K8, level > -30 dBm	< 2 kHz + R&S®FSVA3000/R&S®FSV3000 frequency uncertainty (nom.)
	R&S®VSE-K8, level > -30 dBm	same as the connected device
Carrier frequency drift		
Deviation range	in line with Bluetooth® RF test specification 5.3, 5.1.11; packet type: DH1, DH3, DH5; payload: f1 or f2	±250 kHz
Uncertainty	signal level > -30 dBm	< 2 kHz (nom.)
Adjacent channel power (ACP)		
Measurement		adjacent channel power in line with Bluetooth® RF test specification 5.3, 5.1.8
Level uncertainty	R&S®FSW-K8	same as R&S®FSW
	R&S®FSV3-K8	same as R&S®FSVA3000/R&S®FSV3000
	R&S®VSE-K8	same as the connected device

¹ R&S®FSW with R&S®FSW-B24, R&S®FSVA3000 with R&S®FSV3-B24 or R&S®FSV3000 with R&S®FSV3-B24 RF preamplifier option.

Bluetooth® Enhanced Data Rate measurements

Relative TX power		
Level range	GFSK and DPSK power in line with Bluetooth® RF test specification 5.3, 5.1.12; packet type: 2-DHx, 3-DHx, 2-EVx, 3-EVx	-70 dBm ² to +30 dBm
Level uncertainty	R&S®FSW-K8	same as R&S®FSW
	R&S®FSV3-K8	same as R&S®FSVA3000/R&S®FSV3000
	R&S®VSE-K8	same as the connected device
Frequency stability		
Measurement range	initial frequency error (ω_i), block frequency error (ω_0) and total frequency error ($\omega_i + \omega_0$) in line with Bluetooth® RF test specification 5.3, 5.1.13; packet type: 2-DHx, 3-DHx, 2-EVx, 3-EVx	±250 kHz
Uncertainty	R&S®FSW-K8, initial frequency error, level > -25 dBm	< 2 kHz + R&S®FSW frequency uncertainty (nom.)
	R&S®FSV3-K8, initial frequency error, level > -25 dBm	< 2 kHz + R&S®FSVA3000/R&S®FSV3000 frequency uncertainty (nom.)
	R&S®VSE-K8, initial frequency error, level > -25 dBm	same as the connected device
	block frequency error, level > -25 dBm	< 2 kHz (nom.)
Modulation accuracy		
Measurement range	RMS, peak and 99 % DEVM RF in line with Bluetooth® RF test specification 5.3, 5.1.13; packet type: 2-DHx, 3-DHx, 2-EVx, 3-EVx	0 % to 100 %
Uncertainty	DEVM (RMS), level > -25 dBm	< 2 % (nom.)
	DEVM (peak), level > -25 dBm	< 5 % (nom.)
Inband spurious emissions		
Measurement		adjacent channel power and power between 1 MHz and 1.5 MHz from carrier, in line with Bluetooth® RF test specification 5.3, 5.1.15
Level uncertainty	R&S®FSW-K8	same as R&S®FSW
	R&S®FSV3-K8	same as R&S®FSVA3000/R&S®FSV3000
	R&S®VSE-K8	same as the connected device

² R&S®FSW with R&S®FSW-B24, R&S®FSVA3000 with R&S®FSV3-B24 or R&S®FSV3000 with R&S®FSV3-B24 RF preamplifier option.

Ordering information

Bluetooth® measurement application

Designation	Type	Order No.
Bluetooth® Basic Rate/Enhanced Data Rate/Low Energy measurement application	R&S®FSW-K8	1313.1351.02
Bluetooth® Basic Rate/Enhanced Data Rate/Low Energy measurement application	R&S®FSV3-K8	1346.5679.02
Bluetooth® Basic Rate/Enhanced Data Rate/Low Energy measurement application	R&S®VSE-K8	1345.1970.06

R&S®FSW signal and spectrum analyzer

Designation	Type	Order No.
Base units		
Signal and spectrum analyzer, 2 Hz to 8 GHz	R&S®FSW8	1331.5003.08
Signal and spectrum analyzer, 2 Hz to 13.6 GHz	R&S®FSW13	1331.5003.13
Signal and spectrum analyzer, 2 Hz to 26.5 GHz	R&S®FSW26	1331.5003.26
Signal and spectrum analyzer, 2 Hz to 43.5 GHz	R&S®FSW43	1331.5003.43
Signal and spectrum analyzer, 2 Hz to 50 GHz	R&S®FSW50	1331.5003.50
Signal and spectrum analyzer, 2 Hz to 67 GHz	R&S®FSW67	1331.5003.67
Signal and spectrum analyzer, 2 Hz to 85 GHz	R&S®FSW85	1331.5003.85

R&S®FSVA3000 and R&S®FSV3000 signal and spectrum analyzers

Designation	Type	Order No.
Base units of R&S®FSVA3000 signal and spectrum analyzer		
Signal and spectrum analyzer, 10 Hz to 4 GHz	R&S®FSVA3004	1330.5000.05
Signal and spectrum analyzer, 10 Hz to 7.5 GHz	R&S®FSVA3007	1330.5000.08
Signal and spectrum analyzer, 10 Hz to 13.6 GHz	R&S®FSVA3013	1330.5000.14
Signal and spectrum analyzer, 10 Hz to 30 GHz	R&S®FSVA3030	1330.5000.31
Signal and spectrum analyzer, 10 Hz to 44 GHz	R&S®FSVA3044	1330.5000.44
Signal and spectrum analyzer, 10 Hz to 50/54 GHz	R&S®FSVA3050	1330.5000.51
Base units of R&S®FSV3000 signal and spectrum analyzer		
Signal and spectrum analyzer, 10 Hz to 4 GHz	R&S®FSV3004	1330.5000.04
Signal and spectrum analyzer, 10 Hz to 7.5 GHz	R&S®FSV3007	1330.5000.07
Signal and spectrum analyzer, 10 Hz to 13.6 GHz	R&S®FSV3013	1330.5000.13
Signal and spectrum analyzer, 10 Hz to 30 GHz	R&S®FSV3030	1330.5000.30
Signal and spectrum analyzer, 10 Hz to 44 GHz	R&S®FSV3044	1330.5000.43
Signal and spectrum analyzer, 10 Hz to 50/54 GHz	R&S®FSV3050	1330.5000.50

R&S®RTO1000 and R&S®RTO2000 oscilloscopes

Designation	Type	Order No.
Base units of R&S®RTO1000 oscilloscope		
Oscilloscope, 600 MHz, 10 Gsample/s, 20/40 Msample, 2 channels	R&S®RTO1002	1316.1000.02
Oscilloscope, 600 MHz, 10 Gsample/s, 20/80 Msample, 4 channels	R&S®RTO1004	1316.1000.04
Oscilloscope, 1 GHz, 10 Gsample/s, 20/40 Msample, 2 channels	R&S®RTO1012	1316.1000.12
Oscilloscope, 1 GHz, 10 Gsample/s, 20/80 Msample, 4 channels	R&S®RTO1014	1316.1000.14
Oscilloscope, 2 GHz, 10 Gsample/s, 20/40 Msample, 2 channels	R&S®RTO1022	1316.1000.22
Oscilloscope, 2 GHz, 10 Gsample/s, 20/80 Msample, 4 channels	R&S®RTO1024	1316.1000.24
Oscilloscope, 4 GHz, 20 Gsample/s, 20/80 Msample, 4 channels	R&S®RTO1044	1316.1000.44
Base units of R&S®RTO2000 oscilloscope		
Oscilloscope, 600 MHz, 10 Gsample/s, 50/100 Msample, 2 channels	R&S®RTO2002	1329.7002.02
Oscilloscope, 600 MHz, 10 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2004	1329.7002.04
Oscilloscope, 1 GHz, 10 Gsample/s, 50/100 Msample, 2 channels	R&S®RTO2012	1329.7002.12
Oscilloscope, 1 GHz, 10 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2014	1329.7002.14
Oscilloscope, 2 GHz, 10 Gsample/s, 50/100 Msample, 2 channels	R&S®RTO2022	1329.7002.22
Oscilloscope, 2 GHz, 10 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2024	1329.7002.24
Oscilloscope, 3 GHz, 10 Gsample/s, 50/100 Msample, 2 channels	R&S®RTO2032	1329.7002.32
Oscilloscope, 3 GHz, 10 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2034	1329.7002.34
Oscilloscope, 4 GHz, 20 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2044	1329.7002.44
Oscilloscope, 6 GHz, 20 Gsample/s, 50/200 Msample, 4 channels	R&S®RTO2064	1329.7002.64

R&S®RTP oscilloscope

Designation	Type	Order No.
Base units		
Oscilloscope, 4 GHz, 4 channels	R&S®RTP044	1320.5007.04
Oscilloscope, 6 GHz, 4 channels	R&S®RTP064	1320.5007.06
Oscilloscope, 8 GHz, 4 channels	R&S®RTP084	1320.5007.08
Oscilloscope, 13 GHz, 4 channels	R&S®RTP134	1320.5007.13
Oscilloscope, 16 GHz, 4 channels	R&S®RTP164	1320.5007.16

R&S®VSE vector signal explorer software

Designation	Type	Order No.
R&S®VSE basic edition	R&S®VSE	1345.1011.06
R&S®VSE enterprise edition	R&S®VSE	1345.1105.06
R&S®VSE software maintenance	R&S®VSE-SWM	1320.7622.81

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Rohde & Schwarz is under license.

Service at Rohde & Schwarz
You're in great hands

- ▶ Worldwide
- ▶ Local and personalized
- ▶ Customized and flexible
- ▶ Uncompromising quality
- ▶ Long-term dependability

Rohde & Schwarz

The Rohde&Schwarz technology group is among the trail-blazers when it comes to paving the way for a safer and connected world with its leading solutions in test & measurement, technology systems and networks&cybersecurity. Founded more than 85 years ago, the group is a reliable partner for industry and government customers around the globe. The independent company is headquartered in Munich, Germany and has an extensive sales and service network with locations in more than 70 countries.

www.rohde-schwarz.com

Sustainable product design

- ▶ Environmental compatibility and eco-footprint
- ▶ Energy efficiency and low emissions
- ▶ Longevity and optimized total cost of ownership

Certified Quality Management

ISO 9001

Certified Environmental Management

ISO 14001

Rohde & Schwarz training

www.training.rohde-schwarz.com

Rohde & Schwarz customer support

www.rohde-schwarz.com/support

